

CLAIMS

This is a complete and current listing of the current claims marked with status identifiers in parentheses.

1. (Original) A color display device that determines a relationship between plural color components of an input color image signal in terms of gradation levels of the plural color components of an input color image signal, and that carries out calculation based on the relationship for each of the plural color components excluding a component with a relatively smallest gradation level, using variables varying depending on the respective gradation levels of the plural color components.

2. (Original) A color display device that determines a relationship between three color components of an input color image signal in terms of gradation levels of the three color components of an input color image signal, and that carries out a different calculation for each input color image signal depending on which of six patterns of the relationship that the input color image signal belongs to, the calculation being performed for each of the three color components excluding a component with a relatively smallest gradation level, using variables varying depending on the respective gradation levels of the three color components.

3. (Original) The color display device as set forth in claim 1, wherein:

the variables are determined so that gradation levels of the input color image signal after color compensation fall within a range of a color model that expresses the gradation levels of the input color image signal before and after color compensation in terms of distributions of hue, luminance and saturation.

4. (Original) The color display device as set forth in claim 2, wherein:

the input color image signal is converted into an output color image signal with the at least three color components respectively having gradation levels of r' , g' and b' , which are given by:

$$r' = r + r_o + y_o + m_o,$$

$$g' = g + g_o + y_o + c_o,$$

$$b' = b + b_o + m_o + c_o,$$

where r , g and b are values obtained by dividing original gradation levels of the three color components of the input color image signal by a maximum gradation value $N-1$; and

in a case [1] where $r \geq g \geq b$:

$$r_o = Krg(r-g)^{N_r},$$

$$y_o = Kyg(g-b)^{N_y},$$

$$g_o = b_o = m_o = c_o = 0,$$

in a case [2] where $r \geq b > g$:

$$r_o = Krb(r-b)^{N_r},$$

$$m_o = Kmb(b-g)^{N_m},$$

$$g_o = b_o = y_o = c_o = 0,$$

in a case [3] where $b > r \geq g$:

$$bo = Kbr(b-r)^{Nb},$$

$$mo = Kmr(r-g)^{Nm},$$

$$ro = go = yo = co = 0,$$

in a case [4] where $b > g > r$:

$$bo = Kbg(b-g)^{Nb},$$

$$co = Kcg(g-r)^{Nc},$$

$$ro = go = yo = mo = 0,$$

in a case [5] where $g \geq b > r$:

$$go = Kgb(g-b)^{Ng},$$

$$co = Kcb(b-r)^{Nc},$$

$$ro = bo = yo = mo = 0,$$

in a case [6] where $g > r \geq b$:

$$go = Kgr(g-r)^{Ng},$$

$$yo = Kyr(r-b)^{Ny},$$

$$ro = bo = mo = co = 0,$$

in which Krg , Krb , Kbr , Kbg , Kgb , Kgr , Kyg , Kyr , Kmb , Kmr , Kcg and Kcb are variables which change depending on values of r , g and b ; and Nr , Ng , Nb , Ny , Nm and Nc are constants not less than 0.

5. (Withdrawn) The color display device as set forth in claim 4,
wherein:

the variables are expressed as:

$$Krg = Cr \cdot frg(r, b), Krb = Cr \cdot frb(r, g),$$

$$Kgr = Cg \cdot fgr(g, b), Kgb = Cg \cdot fgb(g, r),$$

$$Kbr = Cb \cdot fbr(b, g), Kbg = Cb \cdot fbg(b, r),$$

$$K_{yg} = C_y \cdot f_{yg}(r, b), K_{mb} = C_m \cdot f_{mb}(r, g),$$

$$K_{mr} = C_m \cdot f_{mr}(b, g), K_{cg} = C_c \cdot f_{cg}(b, r),$$

$$K_{cb} = C_c \cdot f_{cb}(g, r), K_{yr} = C_y \cdot f_{yr}(g, b),$$

where C_r , C_b , C_g , C_y , C_m and C_c are constants; f_{rg} , f_{rb} , f_{gr} , f_{gb} , f_{br} , f_{bg} , f_{yg} , f_{mb} , f_{mr} , f_{cg} , f_{cb} and f_{yr} are functions which respectively change depending on values of r , g and b in corresponding brackets; and the r , g and b are obtained by dividing original gradation levels of the three color components of the input color image signal by a maximum gradation value $N-1$.

6. (Withdrawn) The color display device as set forth in claim 4,
wherein:

the variables are expressed as:

$$K_{rg} = C_r \cdot f_{ar}(r) \cdot f_{ag}(b), K_{rb} = C_r \cdot f_{ar}(r) \cdot f_{ab}(g),$$

$$K_{gr} = C_g \cdot f_{ag}(g) \cdot f_{ar}(b), K_{gb} = C_g \cdot f_{ag}(g) \cdot f_{ab}(r),$$

$$K_{br} = C_b \cdot f_{ab}(b) \cdot f_{ar}(g), K_{bg} = C_b \cdot f_{ab}(b) \cdot f_{ag}(r),$$

$$K_{yg} = C_y \cdot f_{ar}(r) \cdot f_{ab}(b), K_{mb} = C_m \cdot f_{ar}(r) \cdot f_{ag}(g),$$

$$K_{mr} = C_m \cdot f_{ab}(b) \cdot f_{ag}(g), K_{cg} = C_c \cdot f_{ab}(b) \cdot f_{ar}(r),$$

$$K_{cb} = C_c \cdot f_{ag}(g) \cdot f_{ar}(r), K_{yr} = C_y \cdot f_{ag}(g) \cdot f_{ab}(b),$$

where C_r , C_b , C_g , C_y , C_m and C_c are constants; f_{ar} , f_{ab} and f_{ag} are functions which respectively change depending on values of r , g and b in corresponding brackets; and the r , g and b are obtained by dividing original gradation levels of the three color components of the input color image signal by a maximum gradation value $N-1$.

7. (Withdrawn) The color display device as set forth in claim 6,
wherein:
the functions $f_r(r)$, $f_b(b)$ and $f_g(g)$ are continuous functions which give 0
when the r , g and b ($0 \leq r, g, b \leq 1$) are 0 or 1.

8. (Withdrawn) The color display device as set forth in claim 4,
wherein:

the variables are expressed as:

$$K_{rg} = C_r \cdot \alpha_r \cdot \alpha_b, \quad K_{rb} = C_r \cdot \alpha_r \cdot \alpha_g,$$

$$K_{gr} = C_g \cdot \alpha_g \cdot \alpha_b, \quad K_{gb} = C_g \cdot \alpha_g \cdot \alpha_r,$$

$$K_{br} = C_b \cdot \alpha_b \cdot \alpha_g, \quad K_{bg} = C_b \cdot \alpha_b \cdot \alpha_r,$$

$$K_{yg} = C_y \cdot \alpha_r \cdot \alpha_b, \quad K_{mb} = C_m \cdot \alpha_r \cdot \alpha_g,$$

$$K_{mr} = C_m \cdot \alpha_b \cdot \alpha_g, \quad K_{cg} = C_c \cdot \alpha_b \cdot \alpha_r,$$

$$K_{cb} = C_c \cdot \alpha_g \cdot \alpha_r, \quad K_{yr} = C_y \cdot \alpha_g \cdot \alpha_b,$$

$$\alpha_r = f_0 \times r^k \quad (0 \leq r < M_r),$$

$$\alpha_r = f_1 \times (1-r)^k \quad (M_r \leq r \leq 1),$$

$$\alpha_g = g_0 \times g^k \quad (0 \leq g < M_g),$$

$$\alpha_g = g_1 \times (1-g)^k \quad (M_g \leq g \leq 1),$$

$$\alpha_b = h_0 \times b^k \quad (0 \leq b < M_b),$$

$$\alpha_b = h_1 \times (1-b)^k \quad (M_b \leq b \leq 1),$$

where f_0 , f_1 , g_0 , g_1 , h_0 , h_1 , M_r , M_g , M_b and k are constants; C_r , C_b , C_g , C_y , C_m and C_c are constants, and the r , g and b are obtained by dividing original gradation levels of the three color components of the input color image signal by a maximum gradation value $N-1$.

9. (Withdrawn) The color display device as set forth in claim 4,

wherein:

the variables are expressed as:

$$Krg=Cr \cdot ar \cdot ab, \quad Krb=Cr \cdot ar \cdot ag,$$

$$Kgr=Cg \cdot ag \cdot ab, \quad Kgb=Cg \cdot ag \cdot ar,$$

$$Kbr=Cb \cdot ab \cdot ag, \quad Kbg=Cb \cdot ab \cdot ar,$$

$$Kyg=Cy \cdot ar \cdot ab, \quad Kmb=Cm \cdot ar \cdot ag,$$

$$Kmr=Cm \cdot ab \cdot ag, \quad Kcg=Cc \cdot ab \cdot ar,$$

$$Kcb=Cc \cdot ag \cdot ar, \quad Kyr=Cy \cdot ag \cdot ab,$$

$$ar=2 \times r \quad (0 \leq r < 0.5),$$

$$ar=2 \times (1-r) \quad (0.5 \leq r \leq 1),$$

$$ag=2 \times g \quad (0 \leq g < 0.5),$$

$$ag=2 \times (1-g) \quad (0.5 \leq g \leq 1),$$

$$ab=2 \times b \quad (0 \leq b < 0.5),$$

$$ab=2 \times (1-b) \quad (0.5 \leq b \leq 1),$$

where Cr, Cb, Cg, Cy, Cm and Cc are constants, and the r, g and b are obtained by dividing original gradation levels of the three color components of the input color image signal by a maximum gradation value N-1.

10. (Withdrawn) The color display device as set forth in claim 4,

wherein:

the variables are expressed as:

$$Krg=Cr \cdot f_{\max}(r) \cdot f_{\min}(b), \quad Krb=Cr \cdot f_{\max}(r) \cdot f_{\min}(g),$$

$$K_{gr}=C_g \cdot f_{\max}(g) \cdot f_{\min}(b), \quad K_{gb}=C_g \cdot f_{\max}(g) \cdot f_{\min}(r),$$

$$K_{br}=C_b \cdot f_{\max}(b) \cdot f_{\min}(g), \quad K_{bg}=C_b \cdot f_{\max}(b) \cdot f_{\min}(r),$$

$$K_{yg}=C_y \cdot f_{\max}(r) \cdot f_{\min}(b), \quad K_{mb}=C_m \cdot f_{\max}(r) \cdot f_{\min}(g),$$

$$K_{mr}=C_m \cdot f_{\max}(b) \cdot f_{\min}(g), \quad K_{cg}=C_c \cdot f_{\max}(b) \cdot f_{\min}(r),$$

$$K_{cb}=C_c \cdot f_{\max}(g) \cdot f_{\min}(r), \quad K_{yr}=C_y \cdot f_{\max}(g) \cdot f_{\min}(b),$$

where C_r , C_b , C_g , C_y , C_m and C_c are constants; f_{\max} , and f_{\min} are functions which respectively change depending on values of r , g and b in corresponding brackets; and the r , g and b are obtained by dividing original gradation levels of the three color components of the input color image signal by a maximum gradation value $N-1$.

11. (Withdrawn) The color display device as set forth in claim 10, wherein:

the function f_{\max} is a continuous function which gives 0 when the r , g and b ($0 \leq r, g, b \leq 1$) are 1; and the function f_{\min} is continuous function which gives 0 when the r , g and b ($0 \leq r, g, b \leq 1$) are 0.

12. (Withdrawn) The color display device as set forth in claim 4, wherein:

the variables are expressed as:

$$K_{rg}=C_r \cdot S_r \cdot T_b, \quad K_{rb}=C_r \cdot S_r \cdot T_g,$$

$$K_{gr}=C_g \cdot S_g \cdot T_b, \quad K_{gb}=C_g \cdot S_g \cdot T_r,$$

$$K_{br}=C_b \cdot S_b \cdot T_g, \quad K_{bg}=C_b \cdot S_b \cdot T_r,$$

$$K_{yg}=C_y \cdot S_r \cdot T_b, \quad K_{mb}=C_m \cdot S_r \cdot T_g,$$

$$K_{mr}=C_m \cdot S_b \cdot T_g, \quad K_{cg}=C_c \cdot S_b \cdot T_r,$$

$$K_{cb}=C_c \cdot S_g \cdot T_r, \quad K_{yr}=C_y \cdot S_g \cdot T_b,$$

$$T_r=r^k,$$

$$S_r=(1-r)^k,$$

$$T_g=g^k,$$

$$S_g=(1-g)^k,$$

$$T_b=b^k,$$

$$S_b=(1-b)^k,$$

where C_r , C_b , C_g , C_y , C_m , C_c and k are constants, and the r , g and b are obtained by dividing original gradation levels of the three color components of the input color image signal by a maximum gradation value $N-1$.

13. (Withdrawn) The color display device as set forth in claim 12,
wherein:

the constant k is 1.

14. (Withdrawn) The color display device as set forth in claim 5,
wherein:

the C_r , C_b , C_g , C_y , C_m and C_c are constants expressed as $1/(\text{integer power of } 2)$.

15. (Original) The color display device as set forth in claim 4,
wherein:

the variables N_r and N_y are not less than 1.

16. (Original) The color display device as set forth in claim 4,

wherein:

the variables Ng, Nb, Nm and Nc are not more than 1.

17. (Withdrawn) The color display device as set forth in claim 2,

wherein:

the input color image signal is converted into an output color image signal with the three color components respectively having gradation levels of r', g' and b', which are given by:

$$\begin{pmatrix} r' \\ g' \\ b' \end{pmatrix} = \begin{pmatrix} r \\ g \\ b \end{pmatrix} + A_{36} \begin{pmatrix} r_o \\ g_o \\ b_o \\ y_o \\ m_o \\ c_o \end{pmatrix}$$

where r, g and b are values obtained by dividing original gradation levels of the three color components of the input color image signal by a maximum gradation value N-1; and A₃₆ expresses square matrix of 3x6; and

in a case [1] where r≥g≥b:

$$r_o = Krg(r-g)^{N_r},$$

$$y_o = Kyg(g-b)^{N_y},$$

$$g_o = b_o = m_o = c_o = 0,$$

in a case [2] where r≥b>g:

$$r_o = Krb(r-b)^{N_r},$$

$$m_o = Kmb(b-g)^{N_m},$$

$go=bo=yo=co=0,$

in a case [3] where $b>r>g$:

$bo=Kbr(b-r)^{Nb},$

$mo=Kmr(r-g)^{Nm},$

$ro=go=yo=co=0,$

in a case [4] where $b>g>r$:

$bo=Kbg(b-g)^{Nb},$

$co=Kcg(g-r)^{Nc},$

$ro=go=yo=mo=0,$

in a case [5] where $g>b>r$:

$go=Kgb(g-b)^{Ng},$

$co=Kcb(b-r)^{Nc},$

$ro=bo=yo=mo=0,$

in a case [6] where $g>r>b$:

$go=Kgr(g-r)^{Ng},$

$yo=Kyr(r-b)^{Ny},$

$ro=bo=mo=co=0,$

in which $Krg, Krb, Kbr, Kbg, Kgb, Kgr, Kyg, Kyr, Kmb, Kmr, Kcg$ and Kcb are variables which change depending on values of r, g and b ; and Nr, Ng, Nb, Ny, Nm and Nc are constants not less than 0.

18. (Withdrawn) The color display device as set forth in claim 17,
wherein:

the A_{36} is expressed as:

$$A_{36} = \begin{pmatrix} a_{11} & a_{12} & a_{13} & a_{14} & a_{15} & a_{16} \\ a_{21} & a_{22} & a_{23} & a_{24} & a_{25} & a_{26} \\ a_{31} & a_{32} & a_{33} & a_{34} & a_{35} & a_{36} \end{pmatrix}$$

where $a_{11}=a_{22}=a_{33}=a_{14}=a_{24}=a_{15}=a_{35}=a_{26}=a_{36}=1$ and a_{21} , a_{31} , a_{12} , a_{32} , a_{13} , a_{23} , a_{34} , a_{25} and a_{16} are 0 or a negative value.

19. (Withdrawn) The color display device as set forth in claim 17,
wherein:

the A_{36} is expressed as:

$$A_{36} = \begin{pmatrix} a_{11} & a_{12} & a_{13} & a_{14} & a_{15} & a_{16} \\ a_{21} & a_{22} & a_{23} & a_{24} & a_{25} & a_{26} \\ a_{31} & a_{32} & a_{33} & a_{34} & a_{35} & a_{36} \end{pmatrix}$$

where $a_{11}=a_{22}=a_{33}=a_{14}=a_{24}=a_{15}=a_{35}=a_{26}=a_{36}=1$, $a_{11}+a_{21}+a_{31}=0$, $a_{12}+a_{22}+a_{32}=0$, $a_{13}+a_{23}+a_{33}=0$, $a_{14}+a_{24}+a_{34}=0$, $a_{15}+a_{25}+a_{35}=0$, and $a_{16}+a_{26}+a_{36}=0$.

20. (Withdrawn) The color display device as set forth in claim 17,
wherein:

the A_{36} is expressed as:

$$A_{36} = \begin{pmatrix} a_{11} & a_{12} & a_{13} & a_{14} & a_{15} & a_{16} \\ a_{21} & a_{22} & a_{23} & a_{24} & a_{25} & a_{26} \\ a_{31} & a_{32} & a_{33} & a_{34} & a_{35} & a_{36} \end{pmatrix}$$

where $a_{11}=a_{22}=a_{33}=a_{14}=a_{24}=a_{15}=a_{35}=a_{26}=a_{36}=1$,
 $a_{21}=a_{31}=a_{12}=a_{32}=a_{13}=a_{23}=-0.5$, and $a_{34}=a_{25}=a_{16}=-2$.

21. (Original) The color display device as set forth in claim 2,
 wherein:

the input color image signal is converted into an output color image signal
 with the three color components respectively having gradation levels of r' , g' and b' ,
 which are given by:

$$\begin{pmatrix} r' \\ g' \\ b' \end{pmatrix} = \begin{pmatrix} r \\ g \\ b \end{pmatrix} + A_{36} \begin{pmatrix} r_0 \\ g_0 \\ b_0 \\ y_0 \\ m_0 \\ c_0 \end{pmatrix}$$

where r , g and b are values obtained by dividing original gradation levels of
 the three color components of the input color image signal by a maximum
 gradation value $N-1$; and A_{36} expresses square matrix of 3×6 ; and

in a case [1] where $r \geq g \geq b$:

$$r_0 = Krg(fzr(r) - fzg(g))^{Nr},$$

$$y_0 = Kyg(fzg(g) - fzb(b))^{Ny},$$

$$g_0 = b_0 = m_0 = c_0 = 0,$$

in a case [2] where $r \geq b > g$:

$$r_0 = Krb(fzr(r) - fzb(b))^{Nr},$$

$$m_0 = Kmb(fzb(b) - fzg(g))^{Nm},$$

$$g_0 = b_0 = y_0 = c_0 = 0,$$

in a case [3] where $b > r \geq g$:

$$bo = Kbr(fzb(b) - fzb(r))^{Nb},$$

$$mo = Kmr(fzr(r) - fzg(g))^{Nm},$$

$$ro = go = yo = co = 0,$$

in a case [4] where $b > g > r$:

$$bo = Kbg(fzb(b) - fzg(g))^{Nb},$$

$$co = Kcg(fzg(g) - fzr(r))^{Nc},$$

$$ro = go = yo = mo = 0,$$

in a case [5] where $g \geq b > r$:

$$go = Kgb(fzg(g) - fzb(b))^{Ng},$$

$$co = Kcb(fzb(b) - fzr(r))^{Nc},$$

$$ro = bo = yo = mo = 0,$$

in a case [6] where $g > r \geq b$:

$$go = Kgr(fzg(g) - fzr(r))^{Ng},$$

$$yo = Kyr(fzr(r) - fzb(b))^{Ny},$$

$$ro = bo = mo = co = 0,$$

in which Krg, Krb, Kbr, Kbg, Kgb, Kgr, Kyg, Kyr, Kmb, Kmr, Kcg and Kcb are variables which change depending on values of r, g and b, Nr, Ng, Nb, Ny, Nm and Nc are constants not less than 0, and fzb, fzg, fzr are functions which respectively change depending on values of r, g and b in corresponding brackets.

22. (Original) The color display device as set forth in claim 21,
wherein:

the functions fzb, fzg, fzr convert input values identical with each other into output values different from each other.

23. (Original) The color display device as set forth in claim 21,
wherein:

the functions f_zr , f_zg , f_zb satisfy $f_zr=r^{2.2}$, $f_zg=g^{2.2}$ and $f_zb=b^{2.2}$.

24. (Original) The color display device as set forth in claim 21,
wherein:

the functions f_zr , f_zg , f_zb satisfy $f_zr=r^2$, $f_zg=g^2$ and $f_zb=b^2$.

25. (Withdrawn) The color display device as set forth in claim 2,
wherein:

the input color image signal is converted into an output color image signal
with the three color components respectively having gradation levels of r' , g' and b' ,
which are given by:

$$r'=r+ro+yo+mo,$$

$$g'=g+go+yo+co,$$

$$b'=b+bo+mo+co,$$

where r , g and b are values obtained by dividing original gradation levels of
the three color components of the input color image signal by a maximum
gradation value $N-1$; and,

in a case [1] where $r \geq g \geq b$:

$$ro=Krg \cdot fnr(r-g),$$

$$yo=Kyg \cdot fny(g-b),$$

$$go=bo=mo=co=0,$$

in a case [2] where $r \geq b > g$:

$$ro = Krb \cdot fnr(r-b),$$

$$mo = Kmb \cdot fnm(b-g),$$

$$go = bo = yo = co = 0,$$

in a case [3] where $b > r \geq g$:

$$bo = Kbr \cdot fnb(b-r),$$

$$mo = Kmr \cdot fnm(r-g),$$

$$ro = go = yo = co = 0,$$

in a case [4] where $b > g > r$:

$$bo = Kbg \cdot fnb(b-g),$$

$$co = Kcg \cdot fnc(g-r),$$

$$ro = go = yo = mo = 0,$$

in a case [5] where $g \geq b > r$:

$$go = Kgb \cdot fng(g-b),$$

$$co = Kcb \cdot fnc(b-r),$$

$$ro = bo = yo = mo = 0,$$

in a case [6] where $g > r \geq b$:

$$go = Kgr \cdot fng(g-r),$$

$$yo = Kyr \cdot fny(r-b),$$

$$ro = bo = mo = co = 0,$$

in which Krg, Krb, Kbr, Kbg, Kgb, Kgr, Kyg, Kyr, Kmb, Kmr, Kcg and Kcb are variables which change depending on values of r, g and b; and fnr(DX), fng(DX), fnb(DX), fny(DX), fnm(DX) and fnc(DX) are functions which respectively change depending on calculation results DX ($0 \leq DX \leq 1$) of corresponding brackets.

26. (Withdrawn) The color display device as set forth in claim 25,
wherein:

the functions $f_{nr}(DX)$ and $f_{ny}(DX)$ each give a negative value at least at a
predetermined value in a range of $0 < DX \leq 1$.

27. (Withdrawn) The color display device as set forth in claim 25,
wherein:

the functions $f_{nr}(DX)$ and $f_{ny}(DX)$ are expressed as:

$$f_{nr}(DX) = DX^2 - Pr \cdot DX,$$

$$f_{ny}(DX) = DX^2 - Py \cdot DX,$$

where Pr and Py are constants greater than 0.

28. (Withdrawn) The color display device as set forth in claim 2,
wherein:

the input color image signal is converted into an output color image signal
with the three color components respectively having gradation levels of r' , g' and b' ,
which are given by:

$$r' = r + r_o + y_o + m_o,$$

$$g' = g + g_o + y_o + c_o,$$

$$b' = b + b_o + m_o + c_o,$$

where r , g and b are values obtained by dividing original gradation levels of
the three color components of the input color image signal by a maximum
gradation value $N-1$; and,

in a case [1] where $r \geq g \geq b$:

$$r_o = Cr(r-g)^{Nr},$$

$$y_o = C_y(g-b)^{N_y},$$

$$g_o = b_o = m_o = c_o = 0,$$

in a case [2] where $r \geq b > g$:

$$r_o = C_b(r-b)^{N_r},$$

$$m_o = C_m(b-g)^{N_m},$$

$$g_o = b_o = y_o = c_o = 0,$$

in a case [3] where $b > r \geq g$:

$$b_o = C_b(b-r)^{N_b},$$

$$m_o = C_m(r-g)^{N_m},$$

$$r_o = g_o = y_o = c_o = 0,$$

in a case [4] where $b > g > r$:

$$b_o = C_b(b-g)^{N_b},$$

$$c_o = C_c(g-r)^{N_c},$$

$$r_o = g_o = y_o = m_o = 0,$$

in a case [5] where $g \geq b > r$:

$$g_o = C_g(g-b)^{N_g},$$

$$c_o = C_c(b-r)^{N_c},$$

$$r_o = b_o = y_o = m_o = 0, \text{ and}$$

in a case [6] where $g > r \geq b$:

$$g_o = C_g(g-r)^{N_g},$$

$$y_o = C_y(r-b)^{N_y},$$

$$r_o = b_o = m_o = c_o = 0,$$

in which C_r , C_g , C_b , C_y , C_m , C_c , N_r , N_g , N_b , N_y , N_m , and N_c are constants.

29. (Withdrawn) The color display device as set forth in claim 2,

wherein:

the input color image signal is converted into an output color image signal with the three color components respectively having gradation levels of r' , g' and b' , which are given by:

$$\begin{pmatrix} r' \\ g' \\ b' \end{pmatrix} = \begin{pmatrix} r \\ g \\ b \end{pmatrix} + A_{36} \begin{pmatrix} r_o \\ g_o \\ b_o \\ y_o \\ m_o \\ c_o \end{pmatrix}$$

where r , g and b are values obtained by dividing original gradation levels of the three color components of the input color image signal by a maximum gradation value $N-1$; and A_{36} expresses square matrix of 3×6 ; and

in a case [1] where $r \geq g \geq b$:

$$r_o = Cr(r-g),$$

$$y_o = Cy(g-b),$$

$$g_o = b_o = m_o = c_o = 0,$$

in a case [2] where $r \geq b > g$:

$$r_o = Cr(r-b),$$

$$m_o = Cm(b-g),$$

$$g_o = b_o = y_o = c_o = 0,$$

in a case [3] where $b > r \geq g$:

$$b_o = Cb(b-r),$$

$$m_o = Cm(r-g),$$

$$r_o = g_o = y_o = c_o = 0,$$

in a case [4] where $b > g > r$:

$$bo = Cb(b - g),$$

$$co = Cc(g - r),$$

$$ro = go = yo = mo = 0,$$

in a case [5] where $g \geq b > r$:

$$go = Cg(g - b),$$

$$co = Cc(b - r),$$

$$ro = bo = yo = mo = 0, \text{ and}$$

in a case [6] where $g > r \geq b$:

$$go = Cg(g - r),$$

$$yo = Cy(r - b),$$

$$ro = bo = mo = co = 0,$$

in which Cr , Cg , Cb , Cy , Cm , and Cc are constants.

30. (Withdrawn) The color display device as set forth in claim 2,
wherein:

the input color image signal is converted into an output color image signal
with the three color components respectively having gradation levels of r' , g' and b' ,
which are given by:

$$r' = r + ro + yo + mo$$

$$g' = g + go + yo + co$$

$$b' = b + bo + mo + co$$

where r , g and b are values obtained by dividing original gradation levels of
the three color components of the input color image signal by a maximum
gradation value $N-1$; and,

in a case [1] where $(r \geq g \geq b)$:

$$ro = Cr(fzr(r) - fzg(g)),$$

$$yo = Cy(fzg(g) - fzb(b)),$$

$$go = bo = mo = co = 0,$$

in a case [2] where $(r \geq b > g)$:

$$ro = Cr(fzr(r) - fzb(b)),$$

$$mo = Cm(fzb(b) - fzg(g)),$$

$$go = bo = yo = co = 0,$$

in a case [3] where $(b > r \geq g)$:

$$bo = Cb(fzb(b) - fzr(r)),$$

$$mo = Cm(fzr(r) - fzg(g)),$$

$$ro = go = yo = co = 0,$$

in a case [4] where $(b > g > r)$:

$$bo = Cb(fzb(b) - fzg(g)),$$

$$co = Cc(fzg(g) - fzr(r)),$$

$$ro = go = yo = mo = 0,$$

in a case [5] where $(g \geq b > r)$:

$$go = Cg(fzg(g) - fzb(b)),$$

$$co = Cc(fzb(b) - fzr(r)),$$

$$ro = bo = yo = mo = 0, \text{ and}$$

in a case [6] where $(g > r \geq b)$:

$$go = Cg(fzg(g) - fzr(r)),$$

$$yo = Cy(fzr(r) - fzb(b)),$$

$$ro = bo = mo = co = 0,$$

Where C_r , C_g , C_b , C_y , C_m and C_c are constants; and f_{zr} , f_{zg} and f_{zb} are functions which change depending on the values of r , g and b in corresponding brackets.

31. (Original) The color display device as set forth in claim 2,
wherein:

the input color image signal is converted into an output color image signal with the three color components respectively having gradation levels of r' , g' and b' , which are given by:

$$r' = r + r_o + y_o + m_o$$

$$g' = g + g_o + y_o + c_o$$

$$b' = b + b_o + m_o + c_o$$

where r , g and b are values obtained by dividing original gradation levels of the three color components of the input color image signal by a maximum gradation value $N-1$; and,

$$r_o = C_r \cdot \min(r_g, r_b),$$

$$g_o = C_g \cdot \min(g_r, g_b),$$

$$b_o = C_b \cdot \min(b_r, b_g),$$

$$y_o = C_y \cdot \min(r_b, g_b),$$

$$m_o = C_m \cdot \min(r_g, b_g),$$

$$c_o = C_c \cdot \min(g_r, b_r),$$

in which $\min()$ is a function for giving a smallest value in a corresponding bracket; and C_r , C_g , C_b , C_y , C_m and C_c are constants,

on condition that:

$$rg=r-g,$$

$$rb=r-b,$$

$$gr=g-r,$$

$$gb=g-b,$$

$$br=b-r,$$

$$bg=b-g,$$

in which each of rg , rb , gr , gb , br and bg are modified to 0 when they are minus values.

32. (Original) The color display device as set forth in claim 2,
wherein:

the input color image signal is converted into an output color image signal
with the three color components respectively having gradation levels of r' , g' and b' ,
which are given by:

$$r'=r+ro+yo+mo$$

$$g'=g+go+yo+co$$

$$b'=b+bo+mo+co$$

where r , g and b are values obtained by dividing original gradation levels of
the three color components of the input color image signal by a maximum
gradation value $N-1$; and

$$ro=Krg \cdot rg \text{ where } rg < rb,$$

$$ro=Krb \cdot rb \text{ where } rg > rb,$$

$$go=Kgr \cdot gr \text{ where } gr < gb,$$

$$go=Kgb \cdot gb \text{ where } gr > gb,$$

$bo = K_{br} \cdot br$ where $br < bg$,

$bo = K_{bg} \cdot bg$ where $br > bg$,

$yo = K_{yr} \cdot rb$ where $rb < gb$,

$yo = K_{yg} \cdot gb$ where $rb > gb$,

$mo = K_{mr} \cdot rg$ where $rg < bg$,

$mo = K_{mb} \cdot bg$ where $rg > bg$,

$co = K_{cg} \cdot gr$ where $gr < br$,

$co = K_{cb} \cdot br$ where $gr > br$,

in which K_{rg} , K_{rb} , K_{br} , K_{bg} , K_{gb} , K_{gr} , K_{yg} , K_{yr} , K_{mb} , K_{mr} , K_{cg} and K_{cb}
are variables which change depending on values of r , g and b ,

on condition that:

$rg = r - g$,

$rb = r - b$,

$gr = g - r$,

$gb = g - b$,

$br = b - r$,

$bg = b - g$,

in which each of rg , rb , gr , gb , br and bg are modified to 0 when they are
minus values.

33. (Original) A color compensation method, comprising the
steps of:

a) determining a relationship between plural color components of an input color image signal in terms of gradation levels of the plural color components of the input color image signal; and

b) carrying out calculation based on the relationship for each of the plural color components excluding a component with a relatively smallest gradation level, using variables varying depending on the respective gradation levels of the plural color components.

34. (Original) A color compensation method, comprising the steps of:

a) determining a relationship between three color components of an input color image signal in terms of gradation levels of the three color components of the input color image signal; and

b) carrying out a different calculation for each input color image signal depending on which of six patterns of the relationship that the input color image signal belongs to,

wherein:

the calculation in the step (b) is carried out individually for each of the three color components excluding a component with a relatively smallest gradation level, using variables varying depending on the respective gradation levels of the three color components.

35. - 36. (Cancelled).

37. (Original) A storage medium readable by a computer and storing a color compensation program for causing a computer to execute the steps of:

a) determining a relationship between plural color components of an input color image signal in terms of gradation levels of the plural color components of the input color image signal; and

b) carrying out calculation based on the relationship for each of the plural color components excluding a component with a relatively smallest gradation level, using variables varying depending on the respective gradation levels of the plural color components.

38. (Original) A storage medium readable by a computer and storing a color compensation program for causing a computer to execute the steps of:

a) determining a relationship between three color components of an input color image signal in terms of gradation levels of the three color components of the input color image signal; and

b) carrying out a calculation for each input color image signal depending on which of six patterns of the relationship that the input color image signal belongs to, the calculation being carried out individually for each of the three color components excluding a component with a relatively smallest gradation level, using variables varying depending on the respective gradation levels of the three color components.

39. (Withdrawn) A color display device that determines a relationship between plural color components of an input color image signal in terms of gradation levels of the plural color components of the input color image signal, and that carries out calculation based on the relationship, the calculation performing multiplication of each of 1) RGB adjustment components, 2) YMC components as complementary colors of the RGB components and 3) white component, extracted from the plural color components of the input color image signal, by a coefficient, and performing at least one of addition and subtraction of results of the multiplication to the plural color components.

40. (Withdrawn) A color display device that determines a relationship between three color components of an input color image signal in terms of gradation levels of the three color components of an input color image signal, and that carries out a different calculation for each input color image signal depending on which of six patterns of the relationship that the input color image signal belongs to, the calculation performing multiplication of each of 1) RGB adjustment components, 2) YMC components as complementary colors of the RGB components and 3) white component, extracted from the three color components of the input color image signal, by a coefficient, and performing at least one of addition and subtraction of results of the multiplication to the three color components.

41. (Withdrawn) The color display device as set forth in claim 39, wherein:

the color display device carries out the calculation individually for each of the three color components excluding a component with a smallest gradation level, using variables that vary depending on the respective gradation levels of the three color components.

42. (Withdrawn) The color display device as set forth in claim 39, wherein:

the color display device compensates white color by using a coefficient which gives a positive value when the white component of the input color image signal has high luminance and gives a negative value when the white component of the input color image signal has low luminance.

43. (Withdrawn) The color display device as set forth in claim 39, wherein:

the input color image signal is converted into an output color image signal with the three color components respectively having gradation levels of r' , g' and b' , which are given by:

$$r' = r + r_o + y_o + m_o + w_o,$$

$$g' = g + g_o + y_o + c_o + w_o,$$

$$b' = b + b_o + m_o + c_o + w_o,$$

where r , g and b are values obtained by dividing original gradation levels of the three color components of the input color image signal by a maximum gradation value $N-1$; and,

in a case [1] where $r \geq g \geq b$,

$$r_o = Krg(r-g)^{Nr},$$

$$y_o = K_{yg}(g-b)^{N_y},$$

$$w_o = f_w(b),$$

$$g_o = b_o = m_o = c_o = 0,$$

in a case [2] where $r \geq b > g$,

$$r_o = K_{rb}(r-b)^{N_r},$$

$$m_o = K_{mb}(b-g)^{N_m},$$

$$w_o = f_w(g),$$

$$g_o = b_o = y_o = c_o = 0,$$

in a case [3] where $b > r \geq g$,

$$b_o = K_{br}(b-r)^{N_b},$$

$$m_o = K_{mr}(r-g)^{N_m},$$

$$w_o = f_w(g),$$

$$r_o = g_o = y_o = c_o = 0,$$

in a case [4] where $b > g > r$,

$$b_o = K_{bg}(b-g)^{N_b},$$

$$c_o = K_{cg}(g-r)^{N_c},$$

$$w_o = f_w(r),$$

$$r_o = g_o = y_o = m_o = 0,$$

in a case [5] where $g \geq b > r$,

$$g_o = K_{gb}(g-b)^{N_g},$$

$$c_o = K_{cb}(b-r)^{N_c},$$

$$w_o = f_w(r),$$

$$r_o = b_o = y_o = m_o = 0,$$

in a case [6] where $g > r \geq b$,

$$g_o = K_{gr}(g-r)^{N_g},$$

$$y_o = K_{yr}(r-b)^{N_y},$$

$$w_o = fw(b),$$

$$r_o = b_o = m_o = c_o = 0,$$

in which K_{rg} , K_{rb} , K_{br} , K_{bg} , K_{gb} , K_{gr} , K_{yg} , K_{yr} , K_{mb} , K_{mr} , K_{cg} , K_{cb} and k_w are either constants, or variables changing depending on values of r , g and b ; N_r , N_g and N_r are constants not less than 0, and fw is a function which changes depending on the values of r , g and b in the corresponding bracket.

44. (Withdrawn) The color display device as set forth in claim 43,
wherein:

the variables are expressed as:

$$K_{rg} = C_r \cdot \alpha_r \cdot \alpha_b, \quad K_{rb} = C_r \cdot \alpha_r \cdot \alpha_g,$$

$$K_{gr} = C_g \cdot \alpha_g \cdot \alpha_b, \quad K_{gb} = C_g \cdot \alpha_g \cdot \alpha_r,$$

$$K_{br} = C_b \cdot \alpha_b \cdot \alpha_g, \quad K_{bg} = C_b \cdot \alpha_b \cdot \alpha_r,$$

$$K_{yg} = C_y \cdot \alpha_r \cdot \alpha_b, \quad K_{mb} = C_m \cdot \alpha_r \cdot \alpha_g,$$

$$K_{mr} = C_m \cdot \alpha_b \cdot \alpha_g, \quad K_{cg} = C_c \cdot \alpha_b \cdot \alpha_r,$$

$$K_{cb} = C_c \cdot \alpha_g \cdot \alpha_r, \quad K_{yr} = C_y \cdot \alpha_g \cdot \alpha_b,$$

$$\alpha_r = f_0 \times r^k \quad (0 \leq r < M_r),$$

$$\alpha_r = f_1 \times (1-r)^k \quad (M_r \leq r \leq 1),$$

$$\alpha_g = g_0 \times g^k \quad (0 \leq g < M_g),$$

$$\alpha_g = g_1 \times (1-g)^k \quad (M_g \leq g \leq 1),$$

$$\alpha_b = h_0 \times b^k \quad (0 \leq b < M_b),$$

$$\alpha_b = h_1 \times (1-b)^k \quad (M_b \leq b \leq 1),$$

where C_r , C_b , C_g , C_y , C_m and C_c are constants, and the r , g and b are obtained by dividing original gradation levels of the three color components of the input color image signal by a maximum gradation value $N-1$.

45. (Withdrawn) The color display device as set forth in claim 43, wherein:

the variables are expressed as:

$$K_{rg} = C_r \cdot a_r \cdot a_b, \quad K_{rb} = C_r \cdot a_r \cdot a_g,$$

$$K_{gr} = C_g \cdot a_g \cdot a_b, \quad K_{gb} = C_g \cdot a_g \cdot a_r,$$

$$K_{br} = C_b \cdot a_b \cdot a_g, \quad K_{bg} = C_b \cdot a_b \cdot a_r,$$

$$K_{yg} = C_y \cdot a_r \cdot a_b, \quad K_{mb} = C_m \cdot a_r \cdot a_g,$$

$$K_{mr} = C_m \cdot a_b \cdot a_g, \quad K_{cg} = C_c \cdot a_b \cdot a_r,$$

$$K_{cb} = C_c \cdot a_g \cdot a_r, \quad K_{yr} = C_y \cdot a_g \cdot a_b,$$

$$a_r = 2 \times r \quad (0 \leq r < 0.5),$$

$$a_r = 2 \times (1 - r) \quad (0.5 \leq r \leq 1),$$

$$a_g = 2 \times g \quad (0 \leq g < 0.5),$$

$$a_g = 2 \times (1 - g) \quad (0.5 \leq g \leq 1),$$

$$a_b = 2 \times b \quad (0 \leq b < 0.5),$$

$$a_b = 2 \times (1 - b) \quad (0.5 \leq b \leq 1),$$

where C_r , C_b , C_g , C_y , C_m and C_c are constants, and r , g and b are obtained by dividing the original gradation levels of the R, G and B components of the input image signal by the maximum gradation value $N-1$.

46. (Withdrawn) The color display device as set forth in claim 43,
wherein:

the variables are expressed as:

$$Krg=Cr \cdot Sr \cdot Tb, \quad Krb=Cr \cdot Sr \cdot Tg,$$

$$Kgr=Cg \cdot Sg \cdot Tb, \quad Kgb=Cg \cdot Sg \cdot Tr,$$

$$Kbr=Cb \cdot Sb \cdot Tg, \quad Kbg=Cb \cdot Sb \cdot Tr,$$

$$Kyg=Cy \cdot Sr \cdot Tb, \quad Kmb=Cm \cdot Sr \cdot Tg,$$

$$Kmr=Cm \cdot Sb \cdot Tg, \quad Kcg=Cc \cdot Sb \cdot Tr,$$

$$Kcb=Cc \cdot Sg \cdot Tr, \quad Kyr=Cy \cdot Sg \cdot Tb,$$

$$Tr=r^k,$$

$$Sr=(1-r)^k,$$

$$Tg=g^k,$$

$$Sg=(1-g)^k,$$

$$Tb=b^k,$$

$$Sb=(1-b)^k,$$

where Cr, Cb, Cg, Cy, Cm, Cc and k are constants, and r, g and b are obtained by dividing the original gradation levels of the R, G and B components of the input image signal by the maximum gradation value N-1.

47. (Withdrawn) The color display device as set forth in claim 46,
wherein:

the constant k is 1.

48. (Withdrawn) The color display device as set forth in claim 43,
wherein:

the function f_w changes depending on an average luminance and a peak luminance of a whole image.

49. (Withdrawn) The color display device as set forth in claim 43,
wherein:

the function f_w satisfies: $f_w(X) = C_w X^Z$,

where C_w and Z are constants, and X is one of the r , g and b .

50. (Withdrawn) The color display device as set forth in claim 43,
wherein:

the function f_w are expressed as:

$$f_w(X) = C_{w0}X \quad (0 \leq X < M_w),$$

$$f_w(X) = C_{w1}(1-X) \quad (M_w \leq X \leq 1),$$

where C_{w0} , C_{w1} , M_w are constants.

51. (Withdrawn) The color display device as set forth in claim 39,
wherein:

the input color image signal is converted into an output color image signal with the three color components respectively having gradation levels of r' , g' and b' , which are given by:

$$r' = r + r_0 + y_0 + m_0 + w_0$$

$$g' = g + g_0 + y_0 + c_0 + w_0$$

$$b' = b + b_0 + m_0 + c_0 + w_0$$

where r , g and b are values obtained by dividing original gradation levels of the three color components of the input color image signal by a maximum gradation value $N-1$; and

in a case [1] where $(r \geq g \geq b)$:

$$r_o = Cr(r-g),$$

$$y_o = Cy(g-b),$$

$$w_o = fw(b),$$

$$g_o = b_o = m_o = c_o = 0,$$

in a case [2] where $(r \geq b > g)$:

$$r_o = Cr(r-b),$$

$$m_o = Cm(b-g),$$

$$w_o = fw(g),$$

$$g_o = b_o = y_o = c_o = 0,$$

in a case [3] where $(b > r \geq g)$:

$$b_o = Cb(b-r),$$

$$m_o = Cm(r-g),$$

$$w_o = fw(g),$$

$$r_o = g_o = y_o = c_o = 0,$$

in a case [4] where $(b > g > r)$:

$$b_o = Cb(b-g),$$

$$c_o = Cc(g-r),$$

$$w_o = fw(r),$$

$$r_o = g_o = y_o = m_o = 0,$$

in a case [5] where $(g \geq b > r)$:

$$g_o = Cg(g-b),$$

$$co=Cc(b-r),$$

$$wo=fw(r),$$

$$ro=bo=yo=mo=0, \text{ and}$$

in a case [6] where $(g>r>b)$:

$$go=Cg(g-r),$$

$$yo=Cy(r-b),$$

$$wo=fw(b),$$

$$ro=bo=mo=co=0,$$

in which Cr , Cg , Cb , Cy , Cm , and Cc are constants; and fw is a function dynamically changes depending on an average luminance and a peak luminance of a whole image.

52. (Withdrawn) The color display device as set forth in claim 39, wherein:

the input color image signal is converted into an output color image signal with the three color components respectively having gradation levels of r' , g' and b' , which are given by:

$$r'=r+ro+yo+mo+wo$$

$$g'=g+go+yo+co+wo$$

$$b'=b+bo+mo+co+wo$$

where r , g and b are values obtained by dividing original gradation levels of the three color components of the input color image signal by a maximum gradation value $N-1$; and,

$$ro=Cr \cdot \min (rg, rb),$$

$$go=Cg \cdot \min (gr, gb),$$

$$bo = Cb \cdot \min (br, bg),$$

$$yo = Cy \cdot \min (rb, gb),$$

$$mo = Cm \cdot \min (rg, bg),$$

$$co = Cc \cdot \min (gr, br),$$

$$wo = fw \cdot \min (r, g, b),$$

in which $\min ()$ is a function for giving a smallest value in a corresponding bracket,

on condition that:

$$rg = r - g,$$

$$rb = r - b,$$

$$gr = g - r,$$

$$gb = g - b,$$

$$br = b - r,$$

$$bg = b - g,$$

in which each of rg , rb , gr , gb , br and bg are modified to 0 when they are minus values.

53. (Withdrawn) The color display device as set forth in claim 39, wherein:

the input color image signal is converted into an output color image signal with the three color components respectively having gradation levels of r' , g' and b' , which are given by:

$$r' = r + ro + yo + mo + wo$$

$$g' = g + go + yo + co + wo$$

$$b' = b + bo + mo + co + wo$$

where r, g and b are values obtained by dividing original gradation levels of the three color components of the input color image signal by a maximum gradation value N-1; and

$$ro = Krg \cdot rg \text{ where } rg < rb,$$

$$ro = Krb \cdot rb \text{ where } rg > rb,$$

$$go = Kgr \cdot gr \text{ where } gr < gb,$$

$$go = Kgb \cdot gb \text{ where } gr > gb,$$

$$bo = Kbr \cdot br \text{ where } br < bg,$$

$$bo = Kbg \cdot bg \text{ where } br > bg,$$

$$yo = Kyr \cdot rb \text{ where } rb < gb,$$

$$yo = Kyg \cdot gb \text{ where } rb > gb,$$

$$mo = Kmr \cdot rg \text{ where } rg < bg,$$

$$mo = Kmb \cdot bg \text{ where } rg > bg,$$

$$co = Kcg \cdot gr \text{ where } gr < br,$$

$$co = Kcb \cdot br \text{ where } gr > br,$$

$$wo = fw(\min(r, g, b)),$$

in which min () is a function for giving a smallest value in a corresponding bracket; Krg, Krb, Kbr, Kbg, Kgb, Kgr, Kyg, Kyr, Kmb, Kmr, Kcg and Kcb are variables which change depending on values of r, g and b; and fw is a function which changes depending on a value in a corresponding bracket,

on condition that:

$$rg = r - g,$$

$$rb=r-b,$$

$$gr=g-r,$$

$$gb=g-b,$$

$$br=b-r,$$

$$bg=b-g,$$

in which each of rg, rb, gr, gb, br and bg are modified to 0 when they are minus values.

54. (Withdrawn) A color compensation method, comprising the steps of:

a) determining a relationship between plural color components of an input color image signal in terms of their gradation levels; and

b) carrying out calculation based on the relationship, the calculation performing multiplication of each of 1) RGB adjustment components, 2) YMC components as complementary colors of the RGB components and 3) white component, that have been extracted from the plural color components of the input color image signal, by a coefficient, and performing at least one of addition and subtraction of results of the multiplication to the plural color components.

55. (Withdrawn) A color compensation method, comprising the steps of:

a) determining a relationship between three color components of an input color image signal in terms of their gradation levels; and

b) carrying out a different calculation for each input color image signal depending on whether the input color image signal belongs to which of six patterns of the relationship,

wherein the calculation in the step (b) performs multiplication of each of 1) RGB adjustment components, 2) YMC components as complementary colors of RGB components and 3) white component, that have been extracted from the three color components of the input color image signal, by a coefficient, and performs at least one of addition and subtraction of results of the multiplication to the three color components.

56. (Withdrawn) A color compensation program for causing a computer to execute the steps of:

a) determining a relationship between plural color components of an input color image signal in terms of their gradation levels; and

b) carrying out calculation based on the relationship, the calculation performing multiplication of each of 1) RGB adjustment components, 2) YMC components as complementary colors of the RGB components and 3) white component, that have been extracted from the plural color components of the input color image signal, by a coefficient, and performing at least one of addition and subtraction of results of the multiplication to the plural color components.

57. (Withdrawn) A color compensation program for causing a computer to execute the steps of:

a) determining a relationship between three color components of an input color image signal in terms of their gradation levels; and

b) carrying out a different calculation for each input color image signal depending on whether the input color image signal belongs to which of six patterns of the relationship, the calculation performing multiplication of each of 1) RGB adjustment components, 2) YMC components as complementary colors of the RGB components and 3) white component, that have been extracted from the three color components of the input color image signal, by a coefficient, and performing at least one of addition and subtraction of results of the multiplication to the three color components.

58. (Withdrawn) A storage medium readable by a computer and storing a color compensation program for causing a computer to execute the steps of:

a) determining a relationship between plural color components of an input color image signal in terms of their gradation levels; and

b) carrying out calculation based on the relationship, the calculation performing multiplication of each of 1) RGB adjustment components, 2) YMC components as complementary colors of the RGB components and 3) white component, that have been extracted from the plural color components of the input color image signal, by a coefficient, and performing at least one of addition and subtraction of results of the multiplication to the plural color components.

59. (Withdrawn) A storage medium readable by a computer and storing a color compensation program for causing a computer to execute the steps of:

a) determining a relationship between three color components of an input color image signal in terms of their gradation levels; and

b) carrying out a different calculation for each input color image signal depending on whether the input color image signal belongs to which of six patterns of the relationship, the calculation performing multiplication of each of 1) RGB adjustment components, 2) YMC components as complementary colors of the RGB components and 3) white component, that have been extracted from the three color components of the input color image signal, by a coefficient, and performing at least one of addition and subtraction of results of the multiplication to the three color components.

60. (Original) The color display device as set forth in claim 4, further comprising:

 detecting means for detecting environmental changes; and

 color converting means for controlling at least one of the coefficients N_r , N_g , N_b , N_y , N_m , N_c , C_r , C_g , C_b , C_y , C_m , C_c , P_r , P_y and a factor of A_{36} , and the functions f_{zr} , f_{zg} , f_{zb} , f_w , f_{nr} , f_{ng} , f_{nb} , f_{ny} , f_{nm} and f_{nc} , according to a result of detection by the detecting means.

61. (Original) The color display device as set forth in claim 60, wherein:

 the detecting means detects light intensity of outside of the color display device.

62. (Original) The color display device as set forth in claim 4,
further comprising:

color converting means for controlling at least one of the coefficients Nr, Ng,
Nb, Ny, Nm, Nc, Cr, Cg, Cb, Cy, Cm, Cc, Pr, Py and a factor of A_{36} , and the
functions fzr, fzg, fzb, fw, fnr, fng, fnb, fny, fnm and fnc, depending on whether a
backlight of a semi-transmission liquid crystal panel is on or off.

63. (Original) A color display device, comprising:

means for determining a relationship between plural color components of
an input color image signal in terms of the gradation levels of the plural color
components of the input color image signal; and

means for carrying out calculation based on the relationship for each of the
plural color components excluding a component with a relatively smallest gradation
level, using variables varying depending on respective gradation levels of the plural
color components.

64. (Original) The color display device as set forth in claim 63,
wherein:

the variables are determined so that gradation levels of the input color image
signal after color compensation fall within a range of a color model that expresses
the gradation levels of the input color image signal before and after color
compensation in terms of distributions of hue, luminance and saturation.

65. (Original) A color display device, comprising:

means for determining a relationship between three color components of an input color image signal in terms of the gradation levels of the three color components of the input color image signal; and

means for carrying out a calculation for each input color image signal, the calculation being dependent upon which of six patterns of the relationship that the input color image signal belongs to, the calculation further being performed for each of the three color components excluding a component with a relatively smallest gradation level, using variables varying depending on respective gradation levels of the three color components.

66. (Original) A color display method, comprising:

determining a relationship between plural color components of an input color image signal in terms of the gradation levels of the plural color components of the input color image signal; and

carrying out calculation based on the relationship for each of the plural color components excluding a component with a relatively smallest gradation level, using variables varying depending on respective gradation levels of the plural color components.

67. (Original) The color display method as set forth in claim 66,

wherein:

the variables are determined so that gradation levels of the input color image signal after color compensation fall within a range of a color model that expresses the gradation levels of the input color image signal before and after color compensation in terms of distributions of hue, luminance and saturation.

68. (Original) The color display method as set forth in claim 66,
wherein the color display method is for a television receiver.

69. (Cancel).

70. (Cancel).

71. (Currently Amended) A computer readable medium
including program segments for, when executed on a computer device, causing the
computer device to implement the method of claim 66.
~~, comprising the program of claim 69.~~

72. (Original) A color display method, comprising:

determining a relationship between three color components of an input
color image signal in terms of the gradation levels of the three color components of
the input color image signal; and

carrying out a calculation for each input color image signal, the calculation
being dependent upon which of six patterns of the relationship that the input color
image signal belongs to, the calculation further being performed for each of the
three color components excluding a component with a relatively smallest gradation
level, using variables varying depending on respective gradation levels of the three
color components.

73. (Original) The color display method as set forth in claim 72,
wherein the color display method is for a television receiver.

74. (Cancel).

75. (Cancel).

76. (Currently Amended) A computer readable medium
including program segments for, when executed on a computer device, causing the
computer device to implement the method of claim 72.
~~comprising the program of claim 74.~~

77. (Withdrawn) The color display device as set forth in claim 6,
wherein:
the Cr, Cb, Cg, Cy, Cm and Cc are constants expressed as $1/(\text{integer power of } 2)$.

78. (Withdrawn) The color display device as set forth in claim 8,
wherein:
the Cr, Cb, Cg, Cy, Cm and Cc are constants expressed as $1/(\text{integer power of } 2)$.

79. (Withdrawn) The color display device as set forth in claim 9,
wherein:

the Cr, Cb, Cg, Cy, Cm and Cc are constants expressed as $1/(\text{integer power of } 2)$.

80. (Withdrawn) The color display device as set forth in claim 10, wherein:

the Cr, Cb, Cg, Cy, Cm and Cc are constants expressed as $1/(\text{integer power of } 2)$.

81. (Withdrawn) The color display device as set forth in claim 12, wherein:

the Cr, Cb, Cg, Cy, Cm and Cc are constants expressed as $1/(\text{integer power of } 2)$.

82. (Withdrawn) A color display device, comprising:
means for determining a relationship between plural color components of an input color image signal in terms of gradation levels of the plural color components of the input color image signal; and

means for carrying out calculation based on the relationship, the calculation including multiplication of each of 1) RGB adjustment components, 2) YMC components as complementary colors of the RGB components and 3) white component, extracted from the plural color components of the input color image signal, by a coefficient, and including at least one of addition and subtraction of results of the multiplication to the plural color components.

83. (Withdrawn) A color display device, comprising:

means for determining a relationship between three color components of an input color image signal in terms of gradation levels of the three color components of an input color image signal; and

means for carrying out a different calculation for each input color image signal depending on which of six patterns of the relationship that the input color image signal belongs to, the calculation including multiplication of each of 1) RGB adjustment components, 2) YMC components as complementary colors of the RGB components and 3) white component, extracted from the three color components of the input color image signal, by a coefficient, and including at least one of addition and subtraction of results of the multiplication to the three color components.

84. (Withdrawn) A color display method, comprising:

determining a relationship between plural color components of an input color image signal in terms of gradation levels of the plural color components of the input color image signal; and

carrying out calculation based on the relationship, the calculation including multiplication of each of 1) RGB adjustment components, 2) YMC components as complementary colors of the RGB components and 3) white component, extracted from the plural color components of the input color image signal, by a coefficient, and including at least one of addition and subtraction of results of the multiplication to the plural color components.

85. (Withdrawn) The color display method as set forth in claim 84, wherein the color display method is for a television receiver.

86. (Withdrawn) A program, adapted to cause a computer to execute the method of claim 84.

87. (Withdrawn) A computer signal, comprising the program of claim 86.

88. (Withdrawn) A computer readable medium, comprising the program of claim 86.

89. (Withdrawn) A color display method, comprising:
determining a relationship between three color components of an input color image signal in terms of gradation levels of the three color components of an input color image signal; and
carrying out a different calculation for each input color image signal depending on which of six patterns of the relationship that the input color image signal belongs to, the calculation including multiplication of each of 1) RGB adjustment components, 2) YMC components as complementary colors of the RGB components and 3) white component, extracted from the three color components of the input color image signal, by a coefficient, and including at least one of addition and subtraction of results of the multiplication to the three color components.

90. (Withdrawn) The color display method as set forth in claim 89, wherein the color display method is for a television receiver.

91. (Withdrawn) A program, adapted to cause a computer to execute the method of claim 89.

92. (Withdrawn) A computer signal, comprising the program of claim 91.

93. (Withdrawn) A computer readable medium, comprising the program of claim 91.

94. (Withdrawn) The color display device as set forth in claim 40, wherein:

the color display device compensates white color by using a coefficient which gives a positive value when the white component of the input color image signal has high luminance and gives a negative value when the white component of the input color image signal has low luminance.

95. (Withdrawn) The color display device as set forth in claim 40, wherein:

the color display device carries out the calculation individually for each of the three color components excluding a component with a smallest gradation level, using variables that vary depending on the respective gradation levels of the three color components.

96. (Withdrawn) The color display device as set forth in claim 17, further comprising:

detecting means for detecting environmental changes; and
color converting means for controlling at least one of the coefficients Nr, Ng, Nb, Ny, Nm, Nc, Cr, Cg, Cb, Cy, Cm, Cc, Pr, Py and a factor of A_{36} , and the functions f_{zr}, f_{zg}, f_{zb}, f_w, f_{nr}, f_{ng}, f_{nb}, f_{ny}, f_{nm} and f_{nc}, according to a result of detection by the detecting means.

97. (Withdrawn) The color display device as set forth in claim 21, further comprising:
detecting means for detecting environmental changes; and
color converting means for controlling at least one of the coefficients Nr, Ng, Nb, Ny, Nm, Nc, Cr, Cg, Cb, Cy, Cm, Cc, Pr, Py and a factor of A_{36} , and the functions f_{zr}, f_{zg}, f_{zb}, f_w, f_{nr}, f_{ng}, f_{nb}, f_{ny}, f_{nm} and f_{nc}, according to a result of detection by the detecting means.

98. (Withdrawn) The color display device as set forth in claim 25, further comprising:
detecting means for detecting environmental changes; and
color converting means for controlling at least one of the coefficients Nr, Ng, Nb, Ny, Nm, Nc, Cr, Cg, Cb, Cy, Cm, Cc, Pr, Py and a factor of A_{36} , and the functions f_{zr}, f_{zg}, f_{zb}, f_w, f_{nr}, f_{ng}, f_{nb}, f_{ny}, f_{nm} and f_{nc}, according to a result of detection by the detecting means.

99. (Withdrawn) The color display device as set forth in claim 28, further comprising:
detecting means for detecting environmental changes; and

color converting means for controlling at least one of the coefficients Nr, Ng, Nb, Ny, Nm, Nc, Cr, Cg, Cb, Cy, Cm, Cc, Pr, Py and a factor of A_{36} , and the functions f_{zr}, f_{zg}, f_{zb}, f_w, f_{nr}, f_{ng}, f_{nb}, f_{ny}, f_{nm} and f_{nc}, according to a result of detection by the detecting means.

100. (Withdrawn) The color display device as set forth in claim 29, further comprising:
detecting means for detecting environmental changes; and
color converting means for controlling at least one of the coefficients Nr, Ng, Nb, Ny, Nm, Nc, Cr, Cg, Cb, Cy, Cm, Cc, Pr, Py and a factor of A_{36} , and the functions f_{zr}, f_{zg}, f_{zb}, f_w, f_{nr}, f_{ng}, f_{nb}, f_{ny}, f_{nm} and f_{nc}, according to a result of detection by the detecting means.

101. (Withdrawn) The color display device as set forth in claim 30, further comprising:
detecting means for detecting environmental changes; and
color converting means for controlling at least one of the coefficients Nr, Ng, Nb, Ny, Nm, Nc, Cr, Cg, Cb, Cy, Cm, Cc, Pr, Py and a factor of A_{36} , and the functions f_{zr}, f_{zg}, f_{zb}, f_w, f_{nr}, f_{ng}, f_{nb}, f_{ny}, f_{nm} and f_{nc}, according to a result of detection by the detecting means.

102. (Withdrawn) The color display device as set forth in claim 31, further comprising:
detecting means for detecting environmental changes; and

color converting means for controlling at least one of the coefficients Nr, Ng, Nb, Ny, Nm, Nc, Cr, Cg, Cb, Cy, Cm, Cc, Pr, Py and a factor of A_{36} , and the functions fzr, fzg, fzb, fw, fnr, fng, fnb, fny, fnm and fnc, according to a result of detection by the detecting means.

103. (Withdrawn) The color display device as set forth in claim 43, further comprising:
detecting means for detecting environmental changes; and
color converting means for controlling at least one of the coefficients Nr, Ng, Nb, Ny, Nm, Nc, Cr, Cg, Cb, Cy, Cm, Cc, Pr, Py and a factor of A_{36} , and the functions fzr, fzg, fzb, fw, fnr, fng, fnb, fny, fnm and fnc, according to a result of detection by the detecting means.

104. (Withdrawn) The color display device as set forth in claim 17, further comprising:
color converting means for controlling at least one of the coefficients Nr, Ng, Nb, Ny, Nm, Nc, Cr, Cg, Cb, Cy, Cm, Cc, Pr, Py and a factor of A_{36} , and the functions fzr, fzg, fzb, fw, fnr, fng, fnb, fny, fnm and fnc, depending on whether a backlight of a semi-transmission liquid crystal panel is on or off.

105. (Withdrawn) The color display device as set forth in claim 21, further comprising:
color converting means for controlling at least one of the coefficients Nr, Ng, Nb, Ny, Nm, Nc, Cr, Cg, Cb, Cy, Cm, Cc, Pr, Py and a factor of A_{36} , and the

functions fzr, fzg, fzb, fw, fnr, fng, fnb, fny, fnm and fnc, depending on whether a backlight of a semi-transmission liquid crystal panel is on or off.

106. (Withdrawn) The color display device as set forth in claim 25, further comprising:

color converting means for controlling at least one of the coefficients Nr, Ng, Nb, Ny, Nm, Nc, Cr, Cg, Cb, Cy, Cm, Cc, Pr, Py and a factor of A₃₆, and the functions fzr, fzg, fzb, fw, fnr, fng, fnb, fny, fnm and fnc, depending on whether a backlight of a semi-transmission liquid crystal panel is on or off.

107. (Withdrawn) The color display device as set forth in claim 28, further comprising:

color converting means for controlling at least one of the coefficients Nr, Ng, Nb, Ny, Nm, Nc, Cr, Cg, Cb, Cy, Cm, Cc, Pr, Py and a factor of A₃₆, and the functions fzr, fzg, fzb, fw, fnr, fng, fnb, fny, fnm and fnc, depending on whether a backlight of a semi-transmission liquid crystal panel is on or off.

108. (Withdrawn) The color display device as set forth in claim 29, further comprising:

color converting means for controlling at least one of the coefficients Nr, Ng, Nb, Ny, Nm, Nc, Cr, Cg, Cb, Cy, Cm, Cc, Pr, Py and a factor of A₃₆, and the functions fzr, fzg, fzb, fw, fnr, fng, fnb, fny, fnm and fnc, depending on whether a backlight of a semi-transmission liquid crystal panel is on or off.

109. (Withdrawn) The color display device as set forth in claim 30, further comprising:

color converting means for controlling at least one of the coefficients Nr, Ng, Nb, Ny, Nm, Nc, Cr, Cg, Cb, Cy, Cm, Cc, Pr, Py and a factor of A_{36} , and the functions fzr, fzg, fzb, fw, fnr, fng, fnb, fny, fnm and fnc, depending on whether a backlight of a semi-transmission liquid crystal panel is on or off.

110. (Withdrawn) The color display device as set forth in claim 31, further comprising:

color converting means for controlling at least one of the coefficients Nr, Ng, Nb, Ny, Nm, Nc, Cr, Cg, Cb, Cy, Cm, Cc, Pr, Py and a factor of A_{36} , and the functions fzr, fzg, fzb, fw, fnr, fng, fnb, fny, fnm and fnc, depending on whether a backlight of a semi-transmission liquid crystal panel is on or off.

111. (Withdrawn) The color display device as set forth in claim 43, further comprising:

color converting means for controlling at least one of the coefficients Nr, Ng, Nb, Ny, Nm, Nc, Cr, Cg, Cb, Cy, Cm, Cc, Pr, Py and a factor of A_{36} , and the functions fzr, fzg, fzb, fw, fnr, fng, fnb, fny, fnm and fnc, depending on whether a backlight of a semi-transmission liquid crystal panel is on or off.

112. (Withdrawn) A color display method, comprising:
determining a relationship between plural color components of an input color image signal in terms of the gradation levels of the plural color components of the input color image signal; and

carrying out color compensation for flesh colored areas of the input color image signal, the color compensation varying non-linearly in comparison to color compensation carried out for the remainder of the image.

113. (Withdrawn) The color display method of claim 112, wherein color compensation for the remainder of the input color image signal is carried out from a calculation based on the relationship for each of the plural color components excluding a component with a relatively smallest gradation level, using variables varying depending on respective gradation levels of the plural color components.

114. (Withdrawn) The color display method as set forth in claim 113, wherein:

the variables are determined so that gradation levels of the input color image signal after color compensation fall within a range of a color model that expresses the gradation levels of the input color image signal before and after color compensation in terms of distributions of hue, luminance and saturation.

115. (Withdrawn) The color display method as set forth in claim 112, wherein the color display method is for a television receiver.

116. (Withdrawn) A program, adapted to cause a computer to execute the method of claim 112.

117. (Withdrawn) A computer signal, comprising the program of claim 116.

118. (Withdrawn) A computer readable medium, comprising the program of claim 116.

119. (Withdrawn) A color display method, comprising:
determining a relationship between three color components of an input color image signal in terms of the gradation levels of the three color components of the input color image signal; and

carrying out color compensation for flesh colored areas of the input color image signal, the color compensation varying non-linearly in comparison to color compensation carried out for the remainder of the image.

120. (Withdrawn) The color display method of claim 119, wherein color compensation for the remainder of the input color image signal is carried out from a calculation for each input color image signal, the calculation being dependent upon which of six patterns of the relationship that the input color image signal belongs to, the calculation further being performed for each of the three color components excluding a component with a relatively smallest gradation level, using variables varying depending on respective gradation levels of the three color components.

121. (Withdrawn) The color display method as set forth in claim 119, wherein the color display method is for a television receiver.

122. (Withdrawn) A program, adapted to cause a computer to execute the method of claim 119.

123. (Withdrawn) A computer signal, comprising the program of claim 122.

124. (Withdrawn) A computer readable medium, comprising the program of claim 122.

125. (Withdrawn) A color compensation method, comprising the steps of:

a) determining a relationship between plural color components of an input color image signal in terms of gradation levels of the plural color components of the input color image signal; and

b) carrying out color compensation of the input color image signal by controlling a gamma characteristic based upon at least one of average luminance and peak luminance of the input color input signal.

126. (Withdrawn) The color display method of claim 125, wherein color compensation for the remainder of the input color image signal is carried out from a calculation for each input color image signal, the calculation being dependent upon which of six patterns of the relationship that the input color image signal belongs to, the calculation further being performed for each of the three color components excluding a component with a relatively smallest gradation

level, using variables varying depending on respective gradation levels of the three color components.

127. (Withdrawn) The color display method as set forth in claim 125, wherein the color display method is for a television receiver.

128. (Withdrawn) A program, adapted to cause a computer to execute the method of claim 125.

129. (Withdrawn) A computer signal, comprising the program of claim 128.

130. (Withdrawn) A computer readable medium, comprising the program of claim 128.

131. (New) The color display device as set forth in claim 1, wherein:

the gradation level of the color component with the relatively smallest gradation level remains unchanged before and after the calculation.

132. (New) The color display device as set forth in claim 2, wherein:

the relatively greatest component in gradation level among the three components of RGB is compensated by using both the compensation value of the relatively greatest component and the compensation value of the complementary

color of the relatively greatest component and the second relatively greatest component, and the second relatively greatest component in gradation level among the RGB components is compensated by using the compensation value of complementary color of the relatively greatest component and the second relatively greatest component.

133. (New) The computer readable medium as set forth in claim 37, wherein:

the gradation level of the color component with the relatively smallest gradation level remains unchanged before and after the calculation.

134. (New) The computer readable medium as set forth in claim 38, wherein:

the relatively greatest component in gradation level among the three components of RGB is compensated by using both the compensation value of the relatively greatest component and the compensation value of the complementary color of the relatively greatest component and the second relatively greatest component, and the second relatively greatest component in gradation level among the RGB components is compensated by using the compensation value of complementary color of the relatively greatest component and the second relatively greatest component.

135. (New) The color display device as set forth in claim 63, wherein:

the gradation level of the color component with the relatively smallest gradation level remains unchanged before and after the calculation.

136. (New) The color display device as set forth in claim 65, wherein:

the relatively greatest component in gradation level among the three components of RGB is compensated by using both the compensation value of the relatively greatest component and the compensation value of the complementary color of the relatively greatest component and the second relatively greatest component, and the second relatively greatest component in gradation level among the RGB components is compensated by using the compensation value of complementary color of the relatively greatest component and the second relatively greatest component.

137. (New) The color display method as set forth in claim 66, wherein:

the gradation level of the color component with the relatively smallest gradation level remains unchanged before and after the calculation.

138. (New) The color display device as set forth in claim 72, wherein:

the relatively greatest component in gradation level among the three components of RGB is compensated by using both the compensation value of the relatively greatest component and the compensation value of the complementary color of the relatively greatest component and the second relatively greatest

component, and the second relatively greatest component in gradation level among the RGB components is compensated by using the compensation value of complementary color of the relatively greatest component and the second relatively greatest component.